

Reg No.: \_\_\_\_\_

Name: \_\_\_\_\_

**APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY**  
**FIFTH SEMESTER B.TECH DEGREE EXAMINATION, APRIL 2018**

**Course Code: EC303**

**Course Name: APPLIED ELECTROMAGNETIC THEORY (EC)**

Max. Marks: 100


Duration: 3 Hours

**PART A**

*Answer any two full questions, each carries 15 marks*

Marks

- 1 a) State and prove Ampere's law. (6)  
 b) Find the expression for magnetic field intensity at the center of a circular wire carrying current  $I$  in the anticlockwise direction. The radius of the circle is 'a' and the wire is in XY plane. (9)



- 2 a) Define electric field intensity. Derive the equation for electric field intensity at a distance 'r' from a point charge of Q coulombs. (7)  
 b) A charge of  $-0.3\mu\text{C}$  is located at A (25,-30,15) in cm and a second charge of  $0.5\mu\text{C}$  at B (-10, 8, 12). Find E at:  
 i) Origin ii) P (15,20,50) in cm. (8)
- 3 a) Define curl of a vector field. (2)  
 b) Derive the equation for curl of a vector field in Cartesian co-ordinate system. (8)  
 (c) A vector field is given by the following equation  $A = (y \cos ax)a_x + (y + e^x)a_z$ . (5)  
 Find the curl of  $A$  at the origin.

**PART B**

*Answer any two full questions, each carries 15 marks*

- 4 a) Write the general wave equation for a conductive medium and explain each term. (4)  
 b) Define skin depth for a conductive medium? If  $\sigma$  denote the conductivity, Derive the equation for skin depth for a good conductor. (5)  
 c) Find the skin depth,  $\delta$  at a frequency of 1.6 MHz in aluminium, where  $\sigma=38.2\text{MS/m}$  and  $\mu_r = 1$ . Also find the propagation constant,  $\gamma$  and the wave velocity  $v$ . (6)
- 5 a) Derive the equation for Electric and Magnetic field intensities for an electromagnetic wave propagating in the z-direction in a dielectric medium with parameters  $\mu_r, \epsilon_r$ . Find the following: (9)  
 i) Attenuation constant ii) Phase velocity  
 iii) Phase constant iv) Intrinsic impedance

- b) The electric field amplitude of a uniform plane wave propagating in the  $a_z$  direction is 250V/m. If  $E = E_x a_x$  and  $\omega = 1\text{M rad/s}$ . Find: (6)
- i) Frequency      ii) Wavelength  
iii) period      iv) The amplitude of H
- 6 a) Derive the equation for transmission and reflection coefficients of an electromagnetic wave incident normally on the boundary between two different regions. (7)
- (b) A wave propagating in a medium has components  $E = 500 \cos(10^7 t - \beta z) a_x$  V/m (8) and  $H = 1.1 \cos(10^7 t - \beta z) a_y$  A/m. If the wave is travelling at a velocity,  $v = 0.5c$  where 'c' denote velocity of EM wave in free space. Find:
- i)  $\mu_r$    ii)  $\epsilon_r$    iii)  $\beta$    iv)  $\lambda$    v)  $\eta$

### PART C

*Answer any two full questions, each carries 20 marks*

- 7 a) With a neat diagram explain the propagation of electromagnetic wave in a rectangular wave guide? (8)
- b) Derive the equation for electric and magnetic field intensities for TE mode of propagation. (10)
- c) Obtain the cut off frequency for propagation in a rectangular wave guide. (2)
- 8 a) What is characteristic impedance of a transmission line? derive the equation for characteristic impedance of a lossless transmission line. (8)
- b) Write short notes on single stub matching and double stub matching. (8)
- c) How a smith chart is useful in finding the stub length for impedance matching (4)
- 9 a) Derive the equation for characteristic impedance, phase velocity, propagation constant of a transmission line. (12)
- b) At a frequency of 80 MHz, a lossless transmission line has a characteristic impedance of  $300\Omega$  and a wavelength of 2.5m. Find: (8)
- i) L  
ii) C  
iii) If the line is terminated with a parallel combination of  $200\Omega$  and 5pF, determine the reflection co-efficient and the standing wave ratio.

\*\*\*\*