

Reg No.: _____

Name: _____

APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY

Fifth Semester B.Tech Degree Regular and Supplementary Examination December 2020

**Course Code: EC303****Course Name: APPLIED ELECTROMAGNETIC THEORY**

Max. Marks: 100

Duration: 3 Hours

PART A*Answer any two full questions, each carries 15 marks.*

Marks

- 1 a) Derive the expression of energy stored in electric field. (7)
- b) Four 10-nC point charges are located in the $z=0$ plane at the corners of a square 8cm on a side. A fifth 10-nC positive charge is located at a point 8cm distant from each of the other charges. Calculate the magnitude of the total force on the fifth charge for $\epsilon = \epsilon_0$. (8)
- 2 a) Derive the boundary conditions of electric field and magnetic field from Maxwell's equations at the interface of dielectric-dielectric medium. (6)
- b) A lossy dielectric has an intrinsic impedance of $50 \angle 10^\circ \Omega$ at a particular frequency. If at that frequency, the plane wave propagating through the dielectric has the magnetic field component $\mathbf{H} = 10e^{-\alpha y} \cos(\omega t - 5y) \mathbf{a}_x$ A/m find (i) \mathbf{E} (ii) α (iii) Skin depth (9)
- 3 a) State Maxwell's equations in differential form, integral form and mention the laws from which each of the equation is derived. (7)
- b) Derive Continuity equation. (8)

PART B*Answer any two full questions, each carries 15 marks.*

- 4 a) Derive the expression for reflection and transmission coefficients field when a plane wave having parallel polarization is incident obliquely at an angle θ_i on the boundary (z plane) at $x=0$ between medium 1 ($z<0$) characterized by $\mu_1, \epsilon_1, \sigma_1$ and medium 2 ($z>0$) characterized by $\mu_2, \epsilon_2, \sigma_2$. (7)
- b) A 100Ω lossless line is terminated by unknown load impedance Z_L . If at a distance 0.2λ from the load the voltage is $V_S = 1 + 2j$ V while the current is 5mA. Find the load impedance and VSWR. (8)

- 5 a) Derive the expression for voltage, current and input impedance of a transmission line at a distance l from load impedance Z_L (7)
- b) An electromagnetic wave travelling in free space has $E = (5\mathbf{a}_y + 2\mathbf{a}_z)\cos(\omega t + 2y - 4z)$ V/m. Determine (i) ω (ii) λ (iii) The magnetic field component (iv) The time average power. (8)
- 6 a) State Poynting Theorem. Derive the expression for complex Poynting vector. (9)
- b) The propagation constant of a lossy transmission line is $(1 + 2j)m^{-1}$ and its characteristic impedance is 100Ω at $\omega = 10^6$ rad/s. What are the values of L , C , R and G ? (6)

PART C

Answer any two full questions, each carries 20 marks.

- 7 a) If we want to calculate an impedance at 0.4λ from the load using smith chart, how much degree should we move from the load in the smith chart? (8)
- b) Consider a 50Ω , quarter-wave long transmission line at 2GHz. It is connected to a 5V, 10Ω source at one end and is left open circuited at the other end. Calculate the magnitude of voltage at the open circuit end. (12)
- 8 a) Derive expression for TM mode in rectangular wave guide. (10)
- b) A $50 + j75\Omega$ load is connected to 100Ω lossless line. Using smith chart find (i) Reflection coefficient (ii) Standing Wave Ratio (iii) The load admittance Y_L (iv) Z_{in} at 0.5λ from the load. (10)
- 9 a) Derive expression for TE mode in rectangular wave guide. (10)
- b) Consider a TM_{13} propagating inside a rectangular waveguide having $a=5$ cm, $b=6$ cm, $\sigma = 0$, $\mu = \mu_0$, $\epsilon = 9\epsilon_0$ and $H_x = 9\sin(\pi x/a)\cos(3\pi y/b)\sin(2\pi \times 10^{11}t - \beta z)$ A/m. Determine (i) The cut-off frequency (ii) The phase constant (iii) The propagation constant (iv) The intrinsic impedance (10)
